



QUALITEK® Technical Bulletin

RMA Rework Wand

DESCRIPTION

Qualitek® Rework Wands are flux-filled applicator pens designed for hand-soldering assembly or rework applications of circuit boards. RMA Rework Wands have non-corrosive, nonconductive residues.

FEATURES AND BENEFITS

- Easy application of flux to specific areas
- RMA (Rosin Based) flux
- Heat sensitive applicator pen available

TECHNICAL DATA

	Specification
Flux Classification	ROL1
Color and Appearance	Amber liquid
Copper Mirror	Pass
Flash Point	12°C
Solids Content	35.0
Shelf Life	Indefinite

PACKAGING

10ml Flux Pen

CLEANING

For RMA flux pens, since residues are non-corrosive and nonconductive, residues removal is not required. If residue removal is desired, we recommend Everkleen Buffered Saponifier.

STORAGE & SHELF LIFE

Recommended storage is at room temperature away from ignition sources. The shelf life for this product is indefinite.

DISPOSAL

Rework Wands contain hazardous ingredients, therefore, should be disposed of in accordance with local, regional and national requirements.

APPLICATION

Apply pressure to the tip of the Rework Wand to apply the desired amount of flux to a specific area. Apply additional flux as needed.

The information contained herein is based on data considered accurate and is offered at no charge. No warranty is expressed or implied regarding the accuracy of this data. Liability is expressly disclaimed for any loss or injury arising out of the use of this information or the use of the materials designated.

Issue 1 - 23/03/23